



Silver/black



Black/black

## Chorus 32 LED 100 Z

16:9 LCD-TV/ 32" / 80 cm

### Picture technology

Display technology	LCD-TFT w. LED
Diagonal screen size (cm)	80
3D technology	-
Full HD 1920 x 1080	•
200 /100 Hz DMC technology	100 Hz
Max. contrast ratio	700000:1
Automatic contrast of picture content / ambient light	•/•
Panel brightness in cd/m²	360
Typical response time in ms (GTG)	5
Viewing angle type °	178
mecavisionHD+ (incl. 24p) / mecavisionHD (incl. 24p)	-/•
Dual tuner PIP / AV PIP (external sources)	-/-

### Sound technology

Music power output (watts)	2x20
Integrated speakers	2
Bass reflex system / mecaSoundpro / mecaSound+	-/-/•
7 band equalizer	•
Audio output line / variable	•/•
Centre speaker input	-
Dolby Digital+ / HE-AAC	•/-
Automatic volume correction (can be disabled) / separate headphone volume adjustment	•/•

### Operation

Hard disk recorder / Hard disk recorder retrofittable	-/-
Timeshift function	•
USB recording	•
Remote control	RM16
Power switch	•
Local control / Sensor control panel	-/-
LED power light / OLED display	•/-
Electronic programme guide (EPG) for digital channels	•
Tri-Star menu	•

Sleep timer / Child lock	•/•
Data Logic (data dialogue system)	•
Metz Sound System interface / mecahome+	•/•
Top teletext (max. 2,000 pages), TV/teletext split screen	•

#### Reception

Integrated HDTV	•
Equipped with tuner ex works	DVB-C/T/S2
Tuner equipment conversion options	–
Number of CI+ compatible CI slots	1
Max. no. of TV / radio channel presets	3000/3000
Analogue reception via aerial (B/G/H.D/K.L/L.L)	•

#### Internet/Network functions

Metz Media System / HbbTV / Streaming	-
---------------------------------------	---

#### Rear panel connectivity

HDMI port with HDCP / and with ARC	2/-
USB port: quantity / video / photo / audio	-
LAN / Network connection (RJ 45)	-
EURO-AV socket	1
DVI-I (digital and analogue)	-
Audio input / Audio output	•/•
SPDIF digital audio input / SPDIF digital audio output	-/•
USB port for software updates	-
Component input (Y/Pb/Pr, L/R)	-
1 cinch socket for centre channel input	-

#### Lateral connectivity

HDMI port with HDCP / and with ARC	1/-
USB port: quantity / video / photo / audio	1/•/•
VGA	-
Headphone socket	•
Cinch (FBAS)	•
Audio input / Audio output	•/-
USB port for software updates	•

#### Power consumption

Mains voltage	230–240 V/50 Hz
Power consumption in use (in delivery condition) / in standby mode [W]	60,5 / 0,17
Peak luminance ratio	65%
Energy efficiency class	B

#### Dimensions / Weight

Width	79,9
Height incl. base / without base [cm]	60 / 56,7
Depth incl. base / without base [cm]	26 / 8,8
Weight incl. base / without base [kg]	15,4 / 13

#### Other information

Mercury content in mg	0
Device contains lead (within prescribed legal limits)	•